

Transformer Name	Input Voltage	Output Voltage (Volts)	Turns Ratio (X:1)	Nominal Output Termination (preamp input)	Effective input inpedance (ohms)	Attenuation (dB)	Impedance Ratio (X:1)
Peluso T14/1	1	0.057	17.6	1,500	464,640	-24.9	310
Hammond 560 "N" strapped 40K:150	1	0.060	16.7	1,500	418,335	-24.5	279
Peluso BV8P strapped 50 ohm out	1	0.076	13.2	1,500	261,360	-22.4	174
Tab Funkenwerk T14	1	0.080	12.5	1,500	234,375	-21.9	156
Jensen DB-E	1	0.083	12.0	1,500	216,000	-21.6	144
APEX 460 stock transformer	1	0.086	11.6	1,500	201,840	-21.3	135
Cinemag CM-2480	1	0.095	10.5	1,500	165,375	-20.4	110
Hammond 560 "N" strapped 40K:600	1	0.121	8.3	1,500	103,335	-18.4	69
Peluso BV8P strapped 200 ohm out	1	0.152	6.6	1,500	65,340	-16.4	44
Cinemag CM-2461	1	0.153	6.5	1,500	63,375	-16.3	42
Peluso BV11P	1	0.201	5.0	1,500	37,500	-14.0	25